

# Fluke i800 AC Current Clamp Probe



## Key features

- Measures AC current from 100 mA to 800 A rms
- 30 Hz to 10 kHz frequency range
- CAT III 600 V rating
- Accepts up to 54 mm (2.1 in) diameter conductor size
- 1000:1 conversion factor for easy calculation
- Rugged positive action design

## Product overview: Fluke i800 AC Current Clamp Probe

The Fluke i800 AC Current Clamp is designed for use with multimeters, recorders, safety testers, etc., for accurate non-intrusive AC current measurement. It extends the current measuring capability of a digital multimeter to 800 A AC. It is compatible with digital multimeters that accept shrouded 4 mm (0.16) banana plugs and has an AC milliamp range.

## Specifications: Fluke i800 AC Current Clamp Probe

Specifications	
Nominal current range	800 A rms
Continuous current range	100 mA to 800 A rms
Maximum non-destructive current	1500 A rms (50/60 Hz)

Lowest measureable current	100 mA
Basic accuracy	±1% of reading
Useable frequency	30 Hz - 10 kHz (-3dB)
Output level(s)	1 mA / A
<b>Safety Specifications</b>	
Safety	CAT III 600 V
Maximum voltage	600 V AC rms or DC
<b>Mechanical and General Specifications</b>	
Warranty	1 year
Maximum conductor diameter	54 mm (2.13 in)
Output cable length	1.6 m (63 in)
Lead connector	Shrouded banana plugs

## Ordering information



### **Fluke-i800**

AC Current Clamp Probe

---



**Fluke.** *Keeping your world up and running.®*

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**For more information call:**  
In the U.S.A. (800) 443-5853  
In Canada (800) 36-FLUKE  
From other countries +1 (425) 446-5500  
[www.fluke.com](http://www.fluke.com)

©2021 Fluke Corporation.  
Specifications subject to change without notice.  
12/2021

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**