

# Fluke i3000s AC Current Clamp



## Key features

The i3000s is a clamp-on AC Current Clamp for use with oscilloscopes and multimeters with banana input using the supplied Dual Banana to BNC Adapter.

## Product overview: Fluke i3000s AC Current Clamp

### Very High AC Current Clamp

Fluke Current clamps are the ideal tools to extend the current ranges of Fluke tools.

The i3000s is a clamp-on AC Current Clamp for use with oscilloscopes and multimeters with banana input using the supplied Dual Banana to BNC Adapter. The clamp is optimized for measurement on power distribution systems.

## Specifications: Fluke i3000s AC Current Clamp

Specifications	
Nominal current range	30 A 300A 3000A
Continuous current range	1 A - 30 A 1 A - 300 A 1 A - 3000 A

Maximum non-destructive current	4000 A
Lowest measureable current	1 A
Basic accuracy	2% + 2 A (48-65 Hz) % reading + floorspec
Useable frequency	10 Hz - 100 kHz
Output level(s)	10 mv/A 1 mv/A 0.1 mv/A
<b>Safety Specifications</b>	
Safety	CAT III, 600 V
Maximum voltage	600 V AC
<b>Mechanical and General Specifications</b>	
Warranty	1 year
Maximum conductor diameter	64 mm
Output cable length	2.1 m
BNC adapter	Yes

## Ordering information



### **Fluke-i3000s**

Fluke i3000s AC Current Clamp

---

**Fluke.** *Keeping your world up and running.®*

**Fluke Corporation**

PO Box 9090, Everett, WA 98206 U.S.A.

**For more information call:**

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa

+31 (0)40 267 5100

In Canada (905) 890-7600

From other countries +1 (425) 446-5500

**Representative office of Fluke South East Asia Pte Ltd**

C/O Danaher Vietnam

Green Power Tower, 11th Floor Unit 2

35 Ton Duch Thang Street, District 1

Ho Chi Minh City

Vietnam

Tel: +84-8-2220-5371 (ext 103)

Email: [info.asean@fluke.com](mailto:info.asean@fluke.com)

[www.fluke.com/vn-vi](http://www.fluke.com/vn-vi)

©2021 Fluke Corporation. Specifications subject to change without notice.

11/2021

**Modification of this document is not permitted without written permission from Fluke Corporation.**