

Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

Key features

The Fluke TL225 is the solution

- It makes sure the meter has a low input impedance that eliminates stray voltages
- On energized wires, the meter will indicate the real voltage
- On non-energized circuits the meter will read close to zero (even if there are stray voltages)
- It can be used with all modern meters with standard input spacing
- Rated CAT III 1000 V, CAT IV 600 V
- One year warranty

Product overview: Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

Electricians know that when you are measuring electrical installations there often appears to be a voltage, even if you know the wires are non energized. This is called stray or ghost voltages and is caused by the capacity between wires. Because of the very high impedance input of the meter, this stray voltage has nowhere to go which will lead to an incorrect reading on the meter.

The solution is to make sure there is a lower impedance across the input terminals of the meter. However, this is not as easy as it seems since it is vital that the safety of the electrician is not compromised.

Specifications: Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

| Technical Specifications | |
|--------------------------|--|
| Operation temperature | -20°C to +55°C (-40°F to 131°F) |
| Altitude | 2,000 meters operating |
| Humidity | 90% at 0 to 35°C (32°F to 95°F) 70% at 35 to 55°C (95°F to 131°F) |
| Nominal resistance | 3,000 Ω @ 25°C (77°F) |



Ordering information

Fluke. *Keeping your world up and running.®*

Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa +31 (0)40 267 5100

In Canada (800)-36-FLUKE

From other countries +1 (425) 446-5500

Fluke Electronics (Malaysia) Sdn Bhd

Suite D-3A-4, Block D

SouthGage Commercial Centre, No2

Jalan Dua Off Jln Chan Sow Lin

55200 KL

Malaysia

Email: info.asean@fluke.com

www.fluke.com/my

©2021 Fluke Corporation. Specifications subject to change without notice.

11/2021

Modification of this document is not permitted without written permission from Fluke Corporation.