

# Fluke PM8918/301 ScopeMeter Low Pass Filter Probe



## Product overview: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

## Specifications: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

Specifications	
Probe length	2.5m (8 ft.)
Maximum signal voltage	600V rms. CAT III per IEC 1010-2-031
Maximum voltage to ground	600V rms. CAT III per IEC 1010-2-031
Attenuation	10x
Bandwidth	4 kHz
Input resistance	10 MΩ
Input capacitance	12.5pF
Compensation range	15 to 35 pF

When using the mini Test-hooks any potential must not exceed 42 Vpk / 30 Vrms

## Ordering information



### **Fluke PM8918 301**

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

---



**Fluke.** *Keeping your world up and running.®*

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**For more information call:**  
In the U.S.A. (800) 443-5853  
In Canada (800) 36-FLUKE  
From other countries +1 (425) 446-5500  
[www.fluke.com](http://www.fluke.com)

©2021 Fluke Corporation.  
Specifications subject to change without notice.  
11/2021

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**