

Fluke PM8918/301 ScopeMeter Low Pass Filter Probe



Descripción general del producto: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

Especificaciones: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

Specifications	
Probe length	2.5m (8 ft.)
Maximum signal voltage	600V rms. CAT III per IEC 1010-2-031
Maximum voltage to ground	600V rms. CAT III per IEC 1010-2-031
Attenuation	10x
Bandwidth	4 kHz
Input resistance	10 MΩ
Input capacitance	12.5pF



Compensation range	15 to 35 pF
When using the mini Test-hooks any potential must not exceed 42 Vpk / 30 Vrms	

Modelos



Fluke PM8918 301

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

Fluke. Manteniendo su mundo en marcha.

Fluke Corporation

Everett, WA 98206 EE.UU.

Para obtener información adicional En EE. UU. (800) 443-5853

En Europa/Medio Oriente/África

+31 (0)40 267 5100

En Canadá (800)-36-FLUKE

www.fluke.com

Latin America

Tel: +1 (425) 446-5500

www.fluke.com/es-us

©2021 Fluke Corporation. Reservados todos los derechos. Impreso en los Países Bajos. Información sujeta a modificación sin previo aviso.
11/2021

No está permitido modificar este documento sin autorización por escrito de Fluke Corporation.