

Data teknis

Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

Fitur utama

The Fluke TL225 is the solution

- It makes sure the meter has a low input impedance that eliminates stray voltages
- On energized wires, the meter will indicate the real voltage
- On non-energized circuits the meter will read close to zero (even if there are stray voltages)
- It can be used with all modern meters with standard input spacing
- Rated CAT III 1000 V, CAT IV 600 V
- One year warranty

Ikhtisar Produk: Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

Electricians know that when you are measuring electrical installations there often appears to be a voltage, even if you know the wires are non energized. This is called stray or ghost voltages and is caused by the capacity between wires. Because of the very high impedance input of the meter, this stray voltage has nowhere to go which will lead to an incorrect reading on the meter.

The solution is to make sure there is a lower impedance across the input terminals of the meter. However, this is not as easy as it seems since it is vital that the safety of the electrician is not compromised.

Spesifikasi: Fluke TL225 SureGrip™ Stray Voltage Adapter Test Lead Kit

Technical Specifications	
Operation temperature	-20°C to +55°C (-40°F to 131°F)
Altitude	2,000 meters operating
Humidity	90% at 0 to 35°C (32°F to 95°F) 70% at 35 to 55°C (95°F to 131°F)
Nominal resistance	3,000 Ω @ 25°C (77°F)

Model

Fluke. *Memastikan aktivitas Anda terus berjalan dan beroperasi.*

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:
In the U.S.A. (800) 443-5853
In Europe/M-East/Africa
+31 (0)40 267 5100
In Canada (800)-36-FLUKE
From other countries +1 (425) 446-5500
www.fluke.com

BUT. FLUKE SOUTH EAST ASIA PTE LTD
Menera Satu Sentra Kelapa Gading #06-05
JI. Bulevar Kelapa Gading Kav. LA# No. 1
Summarecon Kelapa Gading
Jakarta Utara 14240
Indonesia
Tel: +62 21 2938 5922
Email: info.asean@fluke.com
www.fluke.com/id
©2021 Fluke Corporation. Specifications subject to
change without notice.
12/2021

**Modification of this document is not permitted
without written permission from Fluke Corporation.**