

## Pack de 5 Fluke Volt Alert 1AC II



### Principales fonctions

- Voltbeat™ technology and continuous self-test – so you always know it's working
- Upon detection, tip glows and beeper sounds
- CAT IV 1000 V for added protection
- Expanded range: 90 V AC to 1000 V AC
- 20 V to 90 V AC control circuit model also available
- Two-year warranty
- Batteries included
- On/Off Button
- Audible/Silent
- 5 pack

### Présentation du produit: Pack de 5 Fluke Volt Alert 1AC II

Pack regroupant 5 Fluke VoltAlert™. Prix spécial permettant d'obtenir cinq VoltAlert™ pour le prix de quatre. Un Fluke pour chaque membre de votre équipe !

### Spécifications: Pack de 5 Fluke Volt Alert 1AC II

#### Specifications

Operating principles	Senses the steady state electrostatic field produced by AC voltage through insulation without requiring contact to the bare conductor. A red glow at the tip and a beeping noise (if not switched OFF) indicates the presence of voltage.
Voltage sensing ranges	Nominally, 90 V AC to 1000 V AC
Detector tip style	Flat-tip
Light source	One high intensity red LED
Agency approvals	c CSA us, CE, C-Tick
Safety rating	1000 V, CAT IV
Safety compliance	Meets IEC 61010-1:2001, UL 61010-1 (2nd ed.), CAN/CSA-C22.2 No. 61010-1-04, and ISA-82.02.01 Pollution Degree 2
EMC compliance	Meets IEC 61326-1:2006
IP rating	IP 40
Operating temperature	-10°C to 50°C (-14°F to 122°F)
Operating humidity ranges	0% to 95% (0°C to 30°C)
	0% to 75% (30°C to 40°C)
	0% to 45% (40 to 55°C)
Operating altitude	3000 m
Cleaning	Clean with damp cloth
Batteries	2 AAA alkaline batteries included
Battery life	Typical battery life of greater than 1 year
Warranty period	Two years
Product does not respond to random electrostatic discharge.	

*Soyez à la pointe du progrès avec **Fluke**.*

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**En savoir plus:**  
U.S.A. (800) 443-5853  
Canada (800) 36-FLUKE  
Autre +1 (425) 446-5500  
[www.fluke.com/fr-ca](http://www.fluke.com/fr-ca)

©2022 Fluke Corporation. Tous droits réservés.  
Informations modifiables sans préavis.  
01/2022

**La modification de ce document est interdite sans  
l'autorisation écrite de Fluke Corporation.**