

Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack



Fitur utama

- Low level current clamp measures up to 5 A AC
- Compact shape makes transporting and storing convenient; the clamp measures only 116 x 43 x 23 mm (4.6 x 1.7 x .9 in)
- Take accurate readings without breaking the circuit
- CAT III 600 V (For insulated conductors only)

Ikhtisar Produk: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

A pack of 3 pieces of the i5s current clamps, specially configured to provide low current accuracy while taking measurements on secondary current transformers. This cost-saving 3-pack is perfect for use with 3-phase tools such as the Fluke 434 or Fluke 435.

- Low level current clamp measures up to 5 A ac
- Compact shape makes transporting and storing convenient; the clamp measures only 116 x 43 x 23 mm (4.6 x 1.7 x .9 inches)
- Take accurate readings without breaking the circuit
- CAT III 600 V (For insulated conductors only)

Spesifikasi: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

Specifications

Nominal current range	5 A	
Continuous current range	10 mA to 6 A	
Maximum Non-Destructive Current	70 A	
Lowest measurable current	10 mA	
Basic Accuracy	48 Hz to 65 Hz	
	10 mA to 1 A	1% + 5 mA
	1 A to 5 A	1%
Useable frequency	40 Hz to 5 kHz	
Output level(s)	400 mV/A	
Input Load Impedance	> 1 M Ω in parallel with up to 47 pF	
Crest Factor	≤ 3 , add 0.7% to accuracy	
Safety Specifications		
Safety	CAT III 600 V per IEC/EN61010-1, Pollution Degree 2	
Maximum voltage	600 V ac	
Mechanical & General Specifications		
Warranty	1 year	
Maximum conductor diameter	15 mm	
Output cable length	2.5 m	
BNC Adapter	Yes	
BNC to banana adapter included	No	

Model



Fluke i5sPQ3

5 A ac Current Clamps, 3-pack

Fluke. *Memastikan aktivitas Anda terus berjalan dan beroperasi.*

Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa

+31 (0)40 267 5100

In Canada (800)-36-FLUKE

From other countries +1 (425) 446-5500

www.fluke.com

BUT. FLUKE SOUTH EAST ASIA PTE LTD

Menera Satu Sentra Kelapa Gading #06-05

Jl. Bulevar Kelapa Gading Kav. LA# No. 1

Summarecon Kelapa Gading

Jakarta Utara 14240

Indonesia

Tel: +62 21 2938 5922

Email: info.asean@fluke.com

www.fluke.com/id

©2021 Fluke Corporation. Specifications subject to change without notice.

12/2021

Modification of this document is not permitted without written permission from Fluke Corporation.