

Thông số kỹ thuật

EI-162BN 320 mm Diameter Split Core Transformer



Tính năng chính

External dimensions (LxWxD): 46 x 36 x 16 cm (20.5 x 16 x 17.2 in)
Weight: 8 kg (17.6 lbs)

Tổng quan sản phẩm: EI-162BN 320 mm Diameter Split Core Transformer

Used as a Selective clamp for ground loop resistance measurement around power pylons. Inner diameter of the clamp is 320 mm (12.6 in). Includes the split core transformer. This Split Core Transformer can be used in conjunction with the 1625 Kit* or the 1623 Kit*.

* If non-kit version is owned, the GEOX Probe Cable must be purchased separately.

External dimensions (LxWxD): 46 cm x 36 cm x 16 cm (20.5 in x 16 in x 17.2 in)
Weight: 8 kg (17.6 lbs)

Model



Fluke EI 162BN

320 mm Diameter Split Core Transformer

Fluke. *Giữ cho thế giới của bạn. không ngừng vận động.*

Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa

+31 (0)40 267 5100

In Canada (905) 890-7600

From other countries +1 (425) 446-5500

Representative office of Fluke South East Asia Pte Ltd

C/O Danaher Vietnam

Green Power Tower, 11th Floor Unit 2

35 Ton Duch Thang Street, District 1

Ho Chi Minh City

Vietnam

Tel: +84-8-2220-5371 (ext 103)

Email: info.asean@fluke.com

www.fluke.com/vn

©2022 Fluke Corporation. Specifications subject to change without notice.

01/2022

Modification of this document is not permitted without written permission from Fluke Corporation.